

## Video peripherals for Airtame Hub

In order to run video conferencing calls on Airtame Hub from a meeting room, it will need to be connected to a camera, microphone and a speaker device. We strongly recommend using an integrated microphone+speaker system with echo cancellation and selecting the same device for audio input and output when configuring Airtame Rooms. Airtame Hub can interact with 1 camera, 1 speaker, and 1 microphone device at a time but not two or more devices of the same class simultaneously (Example - 2 cameras cannot be utilized when connected directly to Airtame Hub)

Airtame Hub has three USB 3.0 ports available for connecting video and audio devices (2x USB-A and 1x USB-C) and the device supports a very wide range of products. Each USB port provides 4.5W of output power. Most products that comply with the USB 2.0/3.0 standard and USB Video Class (UVC) and USB Audio Class (UVA) protocols will be supported by Airtame Hub.

## Compatible

The following list of compatible devices have been tested with Airtame Hub either by Airtame or a partner and found to work with the given firmware version. Please see notes for further details on limitations or known issues.

| Vendor   | Product                             | Device Type                           | Firmware     | Remarks  |
|----------|-------------------------------------|---------------------------------------|--------------|--|
| Logitech | <u>Meetup</u>                       | All-In-One Video Bar                  | 1.0.251      | RightSight, RightSense,<br>and Sync are not<br>available with Airtame<br>Hub |
| Logitech | <u>Rally / Rally</u><br><u>Plus</u> | All-In-One Video<br>Conference System | 1.1.148      | RightSight, RightSense,<br>and Sync are not<br>available with Airtame<br>Hub |
| Logitech | <u>Group</u>                        | All-In-One Video<br>Conference System | 9.4          |  |
| Logitech | <u>C930e</u>                        | Camera and<br>Microphone              | 8.1.31       |  |
| Poly     | <u>Studio USB</u>                   | All-In-One Video Bar                  | 1.5.0.000896 |  |

**Airtame ApS** 

Danneskiold-Samsøes Allé 24, 1. tv. 1434 Copenhagen K - DK CVR.: DK35478973 www.airtame.com

| AVer     | VC520 Pro          | All-In-One Video<br>Conference System | 0.0.1006.14        |  |
|----------|--------------------|---------------------------------------|--------------------|--|
| AVer     | VB342+Bar          | All-In-One Video Bar                  | 0.0.0004.08        |  |
| Bose     | <u>VB1</u>         | All-In-One Video Bar                  | 1.2.38_1febf7<br>6 | Low power mode must<br>be turned off either via<br>the Bose Work<br>Configuration app,<br>WebUI or Bose Work<br>Management App to<br>ensure that the camera<br>works on Airtame Hub. |
| Jabra    | Speak 710          | Speakerphone                          | 1.38.0             |  |
| Jabra    | <u>Panacast</u>    | Camera and<br>Microphone              | 1.3.9.15           |  |
| Huddly   | <u>IQ</u>          | Camera and<br>Microphone              | 1.5.4-116286       |  |
| Owl Labs | <u>Meeting Owl</u> | All-In-One Video Bar                  | 0.0.0.1            |  |
| Epos     | <u>SP 30 T</u>     | Speakerphone                          |                    |  |
| Yealink  | UVC84-BYOD         | All-In-One Video<br>Conference System | 262.423.0.25       |  |
| Yealink  | <u>UVC40</u>       | All-In-One Video Bar                  | 128.410.0.30       |  |

CVR.: DK35478973 www.airtame.com

 $\approx$  AIRTAME

April, 2022